
ADAm'sVoice A202 Specifications

Power:	120 VAC 50/60 Hz 6 Watts Max
Size:	13 in. x 9 ½ in. x 3 ½ in.
Output:	2 Watts into an 8 ohm speaker
Signal Inputs:	90 to 150 VAC or VDC or 20 to 30 VAC or VDC.
Signal Formats:	Line per Floor, Binary (0 lowest landing), Binary (1 the lowest landing), Inverse Binary (0), Inverse Binary (1), Binary Coded Decimal, Inverse BCD
Maximum Floors:	Line per Floor – 12 floors; BCD – 99 floors; Binary – 250 floors
Message Triggers:	Two Floor Message Triggers play announcement upon the application of power or the removal of power from the input.
Volume Control:	Dual volume controls so that direction, door closing, and emergency messages play louder than floor announcements.
Direction Messages:	Automatically appends “going up” or “going down” to floor announcement whenever direction inputs are active.
Emergency Messages:	Contains six standard emergency messages. Additional or job specific messages available. Longer lead times and charges may apply.
Emergency Message 1:	Do not be alarmed. This car is needed for a medical emergency. When the doors open, please exit in a safe and orderly manner.
Emergency Message 2:	Do not be alarmed. This car is transferring to emergency power. When the doors open, please exit in a safe and orderly manner.
Emergency Message 3:	Do not be alarmed. This car is now in firefighters return service. When the doors open, please exit in a safe and orderly manner.
Emergency Message 4:	This car is needed for an emergency. When the doors open, please exit in a safe and orderly manner.
Emergency Message 5:	Please exit the car.
Emergency Message 6:	This car is full.
Nudging:	Announces, “Please allow the doors to close.” warning whenever nudging input is active.
Out of Level:	Announces, “Please watch your step.” warning whenever out of level signal is active.
Male Female Voices:	Male, Female, Floor One, First Floor announcements are randomized to minimize listener fatigue.
Languages:	Bi-lingual option plays every message in English and Spanish or English and French.
Memory:	CompactFlash™ memory for up to four hours of messages and safety announcements.
Message Changes:	Fast-N-Easy message upgrades with Adams email option. Coming soon!
Custom Messaging:	For special floor announcements, emergency messages and additional languages contact Adams Parts Sales.